

VoIP Setup Guide for Billion 7404VGPX / VNPX / VGOX / VNOX

1. Open your web browser (e.g. Internet Explorer, Mozilla Firefox, Google Chrome, etc)
2. Enter the following into the address bar: **192.168.1.254**
3. You will be prompted to enter a username and password
 - **Username:** admin
 - **Password:** admin
4. Click on **Login**
5. On the top left menu, click on **Advance**
6. Click on **Configuration**
7. Then click on **VoIP**
8. Then click on **SIP Accounts**
9. Select the **Edit** option for **Phone Port 1**

Edit	Profile Name	Registrar Address	Phone Number	Delete	
<input checked="" type="radio"/>	Phone Port 1	sip.internode.on.net			Sync Now
<input type="radio"/>	Phone Port 2	sip.internode.on.net			Sync Now

10. For **Registrar Address(or Hostname)** - enter your MyNetFone SIP Proxy
11. For **Expire** - enter 120
12. For **User Domain/Realm** - enter your MyNetFone SIP Proxy
13. For **Outbound Proxy Address** - enter your MyNetFone SIP Proxy
14. For **Phone Number** - enter your MyNetFone Number
15. For **Phone Number** - enter your MyNetFone Number
16. For **Password** - enter your MyNetFone Password
17. For **Display Name** - enter your MyNetFone Number

Configuration

▼ SIP Accounts

SIP Setting

Profile Name	Phone Port 1	Registrar Address(or Hostname)	Mynetfone SIP Prox	Registrar Port	5060
Expire(seconds)	120	User Domain/Realm	Mynetfone SIP Prox	Outbound Proxy Address	Mynetfone SIP Prox
Outbound Proxy Port	5060	Phone Number	Mynetfone Number	Username	Mynetfone Number
Password	*****	Display Name	Mynetfone Number		

Add Edit / Delete

Edit	Profile Name	Registrar Address	Phone Number	Delete	
<input checked="" type="radio"/>	Phone Port 1	sip.internode.on.net			Sync Now


18. Click on **Edit / Delete** to apply the changes

19. Select the **Edit** option for **Phone Port 2**

Edit	Profile Name	Registrar Address	Phone Number	Delete	
<input type="radio"/>	Phone Port 1	sip.internode.on.net			Sync Now
<input checked="" type="radio"/>	Phone Port 2	sip.internode.on.net			Sync Now

20. For **Registrar Address(or Hostname)** - enter your MyNetFone SIP Proxy
21. For **Expire** - enter 120
22. For **User Domain/Realm** - enter your MyNetFone SIP Proxy
23. For **Outbound Proxy Address** - enter your MyNetFone SIP Proxy

24. For **Phone Number** - enter your MyNetFone Number
25. For **Phone Number** - enter your MyNetFone Number
26. For **Password** - enter your MyNetFone Password
27. For **Display Name** - enter your MyNetFone Number

Configuration 

▼ SIP Accounts

SIP Setting

Profile Name	Phone Port 2	Registrar Address(or Hostname)	Mynetfone SIP Prox	Registrar Port	5060
Expire(seconds)	120	User Domain/Realm	Mynetfone SIP Prox	Outbound Proxy Address	Mynetfone SIP Prox
Outbound Proxy Port	5060	Phone Number	Mynetfone Number	Username	Mynetfone Number
Password	••••••••	Display Name	Mynetfone Number	Direct in Dial	None

Add Edit / Delete

Edit	Profile Name	Registrar Address	Phone Number	Delete	
<input type="radio"/>	Phone Port 1	sip.internode.on.net			Sync Now
<input checked="" type="radio"/>	Phone Port 2	sip.internode.on.net			Sync Now

28. Click on **Edit / Delete** to apply the changes
29. Click on **Save Config** in the bottom right corner
30. You will be asked to confirm. Click on **Apply** to save your settings (note, it may take up to one minute to save your settings)
31. Click on **Logout** in the bottom right corner