

## VoIP Setup Guide for Billion 7401VGP R3

1. Open your web browser (e.g. Internet Explorer, Mozilla Firefox, Google Chrome, etc)
2. Enter the following into the address bar: 192.168.1.254
3. You will be prompted to enter a username and password
  - **Username:** admin
  - **Password:** admin
4. Click on **Login**
5. On the top left side menu, click on **Advance**
6. Then click on **Configuration**
7. Then click on **VoIP**
8. Then click on **SIP Accounts**
9. Select the **Edit** option

Edit	Profile Name	Registrar Address	Phone Number	Delete	
<input checked="" type="radio"/>	Phone Port 1	sip.internode.on.net			Sync Now

10. For **Registrar Address(or Hostname)** - enter your MyNetFone SIP Proxy
11. Enter 120 for **Expire**
12. For **User Domain/Realm** - enter your MyNetFone SIP Proxy
13. For **Outbound Proxy Address** - enter your MyNetFone SIP Proxy
14. For **Phone Number** - enter your MyNetFone Number
15. For **Username** - enter your MyNetFone Number
16. For **Password** - enter your MyNetFone Password
17. For **Display Name** - enter your MyNetFone Number

**Configuration**

▼ SIP Accounts

SIP Setting

Profile Name	Phone Port 1	Registrar Address(or Hostname)	Mynetfone SIP Prox	Registrar Port	5060
Expire(seconds)	120	User Domain/Realm	Mynetfone SIP Prox	Outbound Proxy Address	Mynetfone SIP Prox
Outbound Proxy Port	5060	Phone Number	Mynetfone Number	Username	Mynetfone Number
Password	*****	Display Name	Mynetfone Number		

Add Edit / Delete

Edit	Profile Name	Registrar Address	Phone Number	Delete	
<input checked="" type="radio"/>	Phone Port 1	sip.internode.on.net			Sync Now

18. Click on **Edit / Delete** to apply the changes.
19. Click on **Save Config** in the bottom right corner
20. You will be asked to confirm. Click on **Apply** to save your settings (note, it may take up to one minute to save your settings)
21. Click on **Logout** in the bottom right corner.