


DSL Setup Guide for Billion 7401VGPM

1. Open your web browser (e.g. Internet Explorer, Mozilla Firefox, Google Chrome, etc)
2. Enter the following into the address bar: **192.168.1.254**
3. You will be prompted to enter a username and password
 - **Username:** admin
 - **Password:** admin
4. Click on **Login**
5. On the left, click on **Quick Start**



6. For **Encapsulation** field - select **PPPoE**
7. For **VPI** - enter 8
8. For **VCI** - enter 35
9. For **Username** - enter your MyNetFone DSL Username (*make sure to use the correct username format e.g. username@dsl.mynetfone.com.au*)
10. For **Password** - enter your MyNetFone DSL Password

Quick Start	
Connection	
Encapsulation	PPPoE <input type="button" value="Auto Scan"/>
VPI	8
VCI	35
NAT	<input checked="" type="radio"/> Enable <input type="radio"/> Disable
Optional Settings	
IP Address	0.0.0.0 <small>('0.0.0.0' means 'Obtain an IP address automatically')</small>
Subnet Mask	0.0.0.0
Default Gateway	
DNS	
Obtain DNS automatically	<input checked="" type="checkbox"/> Enable
Primary DNS	0.0.0.0
Secondary DNS	0.0.0.0
PPP	
Username	username@dsl.mynetfone
Password
<input type="button" value="Apply"/> <input type="button" value="Cancel"/>	

11. Click on **Apply**
12. Click on **Save Config** in the bottom right corner
13. You will be asked to confirm. Click on **Apply** to save your settings (note, it may take up to one minute to save your settings)
14. Click on **Logout** in the bottom right corner