


## VoIP Setup Guide for Billion 7404VGPM / VGOM

1. Open your web browser (e.g. Internet Explorer, Mozilla Firefox, Google Chrome, etc)
2. Enter the following into the address bar: **192.168.1.254**
3. You will be prompted to enter a username and password
  - **Username:** admin
  - **Password:** admin
4. Click on **Login**
5. On the top left side menu, click on **Configuration**
6. Click on **VoIP**
7. Then Click on **General Settings**
8. Navigate to **“Setting for Phone Port 1”**
9. For **Registrar Address(or Hostname)** - enter your MyNetFone SIP Proxy
10. For **Expire** - enter 120
11. For **User Domain/Realm** - enter your MyNetFone SIP Proxy
12. For **Outbound Proxy Address** - enter your MyNetFone SIP Proxy
13. Navigate to **“Setting for Phone Port 2”**
14. For **Registrar Address(or Hostname)** - enter your MyNetFone SIP Proxy
15. For **Expire** - enter 120
16. For **User Domain/Realm** - enter your MyNetFone SIP Proxy
17. For **Outbound Proxy Address** - enter your MyNetFone SIP Proxy
18. Click on **Apply**

General Settings	
SIP Device Parameters <span style="float: right;">Advanced ▾</span>	
SIP	<input checked="" type="radio"/> Enable <input type="radio"/> Disable
Silence Suppression (VAD)	<input type="radio"/> Enable <input checked="" type="radio"/> Disable
Echo Cancellation	<input checked="" type="radio"/> Enable <input type="radio"/> Disable
RTP Port	5100
Region	Australia ▾
Voice QoS, DSCP Marking	Premium ▾
<b>Setting for Phone Port 1</b> <span style="float: right;">Sync Now</span>	
Registrar Address(or Hostname)	Mynetfone SIP Proxy
Registrar Port	5060
Expire	120 seconds
User Domain/Realm	Mynetfone SIP Proxy <small>(If empty, it is the same as Registrar Address.)</small>
Outbound Proxy Address	Mynetfone SIP Proxy <small>(If empty, it is the same as Registrar Address.)</small>
Outbound Proxy Port	5060
<b>Setting for Phone Port 2</b> <span style="float: right;">Sync Now</span>	
Registrar Address(or Hostname)	Mynetfone SIP Proxy
Registrar Port	5060
Expire	120 seconds
User Domain/Realm	Mynetfone SIP Proxy <small>(If empty, it is the same as Registrar Address.)</small>
Outbound Proxy Address	Mynetfone SIP Proxy <small>(If empty, it is the same as Registrar Address.)</small>
Outbound Proxy Port	5060
<p><b>⚠ Please note:</b> VoIP configuration changes will only take effect when you use apply changes and select <b>Sync Now</b> for the relevant line, or when you apply changes, save configuration and restart the device.</p>	
<p style="text-align: center;"> <input type="button" value="Apply"/> <input type="button" value="Cancel"/> </p>	

19. Click on **Phone Port** on the left side menu
20. Click on **Edit** on the right side of **Phone Port 1**


Phone Configuration				
Phone Port				
Index	Phone Number	Display Name	Registered	
1			unknown	<a href="#">Edit ▶</a>
2			unknown	<a href="#">Edit ▶</a>

 *Caution! The VoIP configuration will take effect only when you apply the changes, save configuration and restart the device.*

21. For **Phone Number** - enter your MyNetFone Number
22. For **Authentication Username** - enter your MyNetFone Number
23. For **Password** - enter your MyNetFone Password
24. Re-enter your MyNetFone Password to **Confirm Password**
25. For **Display Name** - enter your MyNetFone Number
26. Click on **Apply**

27. Click on **Edit** on the right side of **Phone Port 2**

Phone Configuration				
Phone Port				
Index	Phone Number	Display Name	Registered	
1			unknown	<a href="#">Edit ▶</a>
2			unknown	<a href="#">Edit ▶</a>

 *Caution! The VoIP configuration will take effect only when you apply the changes, save configuration and restart the device.*

28. For **Phone Number** - enter your MyNetFone Number
29. For **Authentication Username** - enter your MyNetFone Number
30. For **Password** - enter your MyNetFone Password
31. Re-enter your MyNetFone Password to **Confirm Password**
32. For **Display Name** - enter your MyNetFone Number
33. Click on **Apply**
34. Click on **Save Config** in the bottom right corner
35. You will be asked to confirm. Click on **Apply** to save your settings (note, it may take up to one minute to save your settings)
36. Click on **Logout** in the bottom right corner